

技术资料 Technical Data

KSS 出线孔配线槽电线容量 KSS Wiring Duct (Slotted) Wirefill Capacity

| 配线槽尺寸 | | 电线称呼 | | 0.75mm ² | 1.25mm ² | 2mm ² | 3.5mm ² | 5.5mm ² | 8mm ² | 14mm ² | 22mm ² | 网路线 | |
|-------|-----|------------------|-------------|---------------------|---------------------|------------------|--------------------|--------------------|------------------|-------------------|-------------------|---------|--------|
| W | H | 外径 mm | | 22-20AWG | 22-16AWG | 16-14AWG | 12AWG | 12-10AWG | 8AWG | 6AWG | 4AWG | Cat. 5e | Cat. 6 |
| 15 | 25 | 建议使用配线槽 60%空间 | 电线容量 pcs | 30 | 25 | 19 | 14 | 9 | 6 | 3 | 2 | 10 | 5 |
| 20 | 20 | | | 32 | 26 | 20 | 15 | 9 | 6 | 4 | 2 | 11 | 6 |
| 25 | 25 | | | 51 | 41 | 32 | 23 | 15 | 10 | 6 | 4 | 17 | 9 |
| 25 | 30 | | | 61 | 50 | 38 | 28 | 18 | 12 | 7 | 5 | 21 | 11 |
| 25 | 40 | | | 82 | 66 | 51 | 37 | 24 | 16 | 10 | 7 | 28 | 15 |
| 25 | 45 | | | 92 | 75 | 58 | 42 | 27 | 18 | 11 | 7 | 31 | 17 |
| 25 | 50 | | | 102 | 83 | 64 | 46 | 30 | 20 | 12 | 8 | 35 | 18 |
| 25 | 60 | | | 123 | 100 | 77 | 56 | 36 | 25 | 15 | 10 | 42 | 22 |
| 25 | 65 | | | 133 | 108 | 84 | 60 | 39 | 27 | 16 | 11 | 46 | 24 |
| 25 | 75 | | | 154 | 125 | 97 | 70 | 45 | 31 | 19 | 13 | 53 | 28 |
| 25 | 80 | | | 164 | 133 | 103 | 75 | 48 | 33 | 20 | 14 | 56 | 30 |
| 30 | 30 | | | 74 | 60 | 46 | 33 | 21 | 15 | 9 | 6 | 25 | 13 |
| 30 | 60 | | | 148 | 120 | 93 | 67 | 43 | 30 | 18 | 12 | 51 | 27 |
| 30 | 80 | | | 197 | 160 | 124 | 90 | 57 | 40 | 24 | 17 | 68 | 36 |
| 33 | 33 | | | 89 | 72 | 56 | 40 | 26 | 18 | 11 | 7 | 30 | 16 |
| 33 | 40 | | | 108 | 88 | 68 | 49 | 31 | 22 | 13 | 9 | 37 | 19 |
| 33 | 45 | | | 122 | 99 | 77 | 55 | 35 | 24 | 15 | 10 | 42 | 22 |
| 33 | 60 | | | 162 | 132 | 102 | 74 | 47 | 33 | 20 | 14 | 56 | 29 |
| 33 | 65 | | | 176 | 143 | 111 | 80 | 51 | 35 | 22 | 15 | 60 | 32 |
| 33 | 100 | | | 271 | 220 | 171 | 123 | 79 | 55 | 34 | 23 | 93 | 49 |
| 37.5 | 100 | 308 | 250 | 194 | 140 | 90 | 62 | 38 | 26 | 106 | 56 | | |
| 38 | 25 | 78 | 63 | 49 | 35 | 22 | 15 | 9 | 6 | 26 | 14 | | |
| 38 | 50 | 156 | 126 | 98 | 71 | 45 | 31 | 19 | 13 | 53 | 28 | | |
| 38 | 75 | 234 | 190 | 147 | 106 | 68 | 47 | 29 | 20 | 80 | 43 | | |
| 40 | 20 | 65 | 53 | 41 | 30 | 19 | 13 | 8 | 5 | 22 | 12 | | |
| 40 | 40 | 131 | 106 | 83 | 60 | 38 | 26 | 16 | 11 | 45 | 24 | | |
| 40 | 60 | 197 | 160 | 124 | 90 | 57 | 40 | 24 | 17 | 68 | 36 | | |
| 40 | 65 | 213 | 173 | 134 | 97 | 62 | 43 | 27 | 18 | 73 | 39 | | |
| 40 | 80 | 263 | 213 | 166 | 120 | 76 | 53 | 33 | 22 | 90 | 48 | | |
| 40 | 100 | 329 | 266 | 207 | 150 | 96 | 66 | 41 | 28 | 113 | 60 | | |
| 45 | 45 | 166 | 135 | 105 | 75 | 48 | 33 | 21 | 14 | 57 | 30 | | |
| 45 | 65 | 240 | 195 | 151 | 109 | 70 | 48 | 30 | 20 | 82 | 44 | | |
| 48 | 60 | 237 | 192 | 149 | 108 | 69 | 48 | 29 | 20 | 81 | 43 | | |
| 48 | 100 | 395 | 320 | 249 | 180 | 115 | 80 | 49 | 34 | 136 | 72 | | |
| 50 | 50 | 205 | 166 | 129 | 93 | 60 | 41 | 25 | 17 | 70 | 37 | | |
| 50 | 75 | 308 | 250 | 194 | 140 | 90 | 62 | 38 | 26 | 106 | 56 | | |

技术资料 Technical Data

KSS 出线孔配线槽电线容量 KSS Wiring Duct (Slotted) Wirefill Capacity

| 配线槽尺寸 | | 电线称呼 | | 0.75mm ² | 1.25mm ² | 2mm ² | 3.5mm ² | 5.5mm ² | 8mm ² | 14mm ² | 22mm ² | 网路线 | |
|-------|-----|----------------------|-------------|---------------------|---------------------|------------------|--------------------|--------------------|------------------|-------------------|-------------------|---------|--------|
| W | H | 外径 mm | | 2.7 | 3.0 | 3.4 | 4.0 | 5.0 | 6.0 | 7.6 | 9.2 | Cat. 5e | Cat. 6 |
| 55 | 100 | 建议使用配线槽 60% 空间 | 电线容量 pcs | 452 | 366 | 285 | 206 | 132 | 91 | 57 | 38 | 155 | 83 |
| 60 | 40 | | | 197 | 160 | 124 | 90 | 57 | 40 | 24 | 17 | 68 | 36 |
| 60 | 60 | | | 296 | 240 | 186 | 135 | 86 | 60 | 37 | 25 | 102 | 54 |
| 60 | 80 | | | 395 | 320 | 249 | 180 | 115 | 80 | 49 | 34 | 136 | 72 |
| 60 | 100 | | | 493 | 400 | 311 | 225 | 144 | 100 | 62 | 42 | 170 | 90 |
| 65 | 45 | | | 240 | 195 | 151 | 109 | 70 | 48 | 30 | 20 | 82 | 44 |
| 65 | 65 | | | 347 | 281 | 219 | 158 | 101 | 70 | 43 | 29 | 119 | 63 |
| 70 | 40 | | | 230 | 186 | 145 | 105 | 67 | 46 | 29 | 19 | 79 | 42 |
| 70 | 100 | | | 576 | 466 | 363 | 262 | 168 | 116 | 72 | 49 | 198 | 105 |
| 72 | 64 | | | 379 | 307 | 239 | 172 | 110 | 76 | 47 | 32 | 130 | 69 |
| 75 | 40 | | | 246 | 200 | 155 | 112 | 72 | 50 | 31 | 21 | 85 | 45 |
| 75 | 50 | | | 308 | 250 | 194 | 140 | 90 | 62 | 38 | 26 | 106 | 56 |
| 75 | 75 | | | 462 | 375 | 291 | 210 | 135 | 93 | 58 | 39 | 159 | 85 |
| 75 | 100 | | | 617 | 500 | 389 | 281 | 180 | 125 | 77 | 53 | 212 | 113 |
| 80 | 40 | | | 263 | 213 | 166 | 120 | 76 | 53 | 33 | 22 | 90 | 48 |
| 80 | 60 | | | 395 | 320 | 249 | 180 | 115 | 80 | 49 | 34 | 136 | 72 |
| 80 | 80 | | | 526 | 426 | 332 | 240 | 153 | 106 | 66 | 45 | 181 | 96 |
| 80 | 100 | | | 658 | 533 | 415 | 300 | 192 | 133 | 83 | 56 | 226 | 120 |
| 100 | 40 | | | 329 | 266 | 207 | 150 | 96 | 66 | 41 | 28 | 113 | 60 |
| 100 | 50 | | | 411 | 333 | 259 | 187 | 120 | 83 | 51 | 35 | 141 | 75 |
| 100 | 60 | | | 493 | 400 | 311 | 225 | 144 | 100 | 62 | 42 | 170 | 90 |
| 100 | 75 | | | 617 | 500 | 389 | 281 | 180 | 125 | 77 | 53 | 212 | 113 |
| 100 | 80 | | | 658 | 533 | 415 | 300 | 192 | 133 | 83 | 56 | 226 | 120 |
| 100 | 100 | | | 823 | 666 | 519 | 375 | 240 | 166 | 103 | 70 | 283 | 151 |
| 120 | 60 | | | 592 | 480 | 373 | 270 | 172 | 120 | 74 | 51 | 204 | 108 |
| 120 | 65 | | | 641 | 520 | 404 | 292 | 187 | 130 | 81 | 55 | 221 | 117 |
| 120 | 75 | | | 740 | 600 | 467 | 337 | 216 | 150 | 93 | 63 | 255 | 136 |
| 120 | 80 | | | 790 | 640 | 498 | 360 | 230 | 160 | 99 | 68 | 272 | 145 |
| 150 | 75 | 925 | 750 | 583 | 421 | 270 | 187 | 116 | 79 | 318 | 170 | | |
| 150 | 100 | 1234 | 1000 | 778 | 562 | 360 | 250 | 155 | 106 | 425 | 226 | | |
| 200 | 100 | 1646 | 1333 | 1038 | 750 | 480 | 333 | 207 | 141 | 567 | 302 | | |
| 200 | 150 | 2469 | 2000 | 1557 | 1125 | 720 | 500 | 311 | 212 | 850 | 453 | | |
| 200 | 200 | 3292 | 2666 | 2076 | 1500 | 960 | 666 | 415 | 283 | 1134 | 604 | | |
| 300 | 100 | 2469 | 2000 | 1557 | 1125 | 720 | 500 | 311 | 212 | 850 | 453 | | |

实际电线容量可能与理论值有所误差，如有不符，以实际状况为主。